

Specifications

In the box

- Manta TR1 unit
- USB cable: 150cm (~5 feet)
- Setup Instructions

Ports

- Mini USB-B port
- Two IR-Blaster ports
(3.5mm minijacks)

Communication

- Input: Consumer Infrared (cIR) signals
- Distance: up to 10m (33 feet)

IR Frequency

- Receiving: 31 - 60 kHz

Electrical Requirements

- 4.5 - 5.25v (from USB)
 - 500ma (normal)
 - 100ma (sleep)

Warranty

- 1 Year warranty

Dimensions

- Length: 48mm (1.9 inches)
- Width: 48mm (1.9 inches)
- Height: 20mm (0.8 inches)

Hardware Requirements

- Windows/Linux-based PC or D-Link Boxee Box
- Available USB port
- Universal Remote or Media Center Remote

Supported Remotes

- Windows Media Center Remotes (All RC-6 protocol)
- Logitech Harmony (All)
- URC Remotes (Most models)
- Philips Pronto
- Philips Prestigo
- RTI
- One4All (including JP1)
- UEI Nevo
- Other (5 year or newer) Universal Remotes

Supported HTPC/Media Software

- Windows Media Center
- XBMC
- Plex
- SageTV
- JRiver Media Center
- MediaPortal
- Boxee
- MythTV
- Windows Media Player
- and more...

Supported Customization Software

- Event Ghost
- Girdir
- HiP
- IRServer Suite
- LM Remote Keymap
- Lirc

* Boxee Box cannot be turned ON with external devices.
PC Systems support wake from S1 and S3 sleep/suspend.